

How to setup VOIP on a THOMSON ST706 or ST 780 WL for 3starsnet

The THOMSON ST706 has 1 phone out connector, the ST 780 WL has 2 phone connectors and 1 FXO port to connect your classic active PSTN telephone line,

SpeedTouch - Toolbox - Mozilla Firefox

Bestand Bewerken Beeld Geschiedenis Bladwijzers Extra Help

http://192.168.1.254/cgi/b/toolbox/?be=0&l0=2&l1=-1

THOMSON ST706 THOMSON images & beyond

[admin] Home > Toolbox Help

SpeedTouch

Broadband Connection

Toolbox

- Remote Assistance
- Address Book
- **Telephony**
- Game & Application Sharing
- Parental Control
- Firewall
- Intrusion Detection
- Dynamic DNS
- User Management

Home Network

Toolbox

Your SpeedTouch device offers multiple services. Those services enable you to protect your device, other people on the Internet, or manage your communications with...

Remote Assistance Disabled

Address Book Disabled

Telephony Disabled

Game & Application Sharing UPnP: Enabled

Parental Control Address Filtering: Disabled

Firewall Security Level: Standard

Intrusion Detection Enabled

Dynamic DNS Enabled

User Management Logged In As: admin [Switch User](#)

javascript:GoAndRemember('/cgi/b/voip_ovp/')

1000+

SpeedTouch - SIP - Mozilla Firefox

Bestand Bewerken Beeld Geschiedenis Bladwijzers Extra Help

http://192.160.1.254/cgi/bf/_voip_/cfg/?be=0&l0=2&l1=2

THOMSON ST706

THOMSON
images & beyond

[admin]
Home > Toolbox > Telephony

Overview | Details | Configure | Expert Configure | Help

SpeedTouch

Broadband Connection

Toolbox

- Remote Assistance
- Address Book
- **Telephony**
- Game & Application Sharing
- Parental Control
- Firewall
- Intrusion Detection
- Dynamic DNS
- User Management

Home Network

Telephony

- Service Configuration
Enable Telephone:
- Telephone Numbers

SIP URI: 024XXXXXX

Username: 024XXXXXX

Password: ●●●●●

Confirm Password: ●●●●●

Displayname: Jean-Louis Michel

Abbreviated number: 024XXXXXXXXX

Port: Phone 1

Apply Cancel

Pick a task...

- > [View telephony statistics and logs](#)
- > [View telephony services](#)
- > [Address book](#)

Klaar

ARP 1000+

Go to "configure"

Enable phone service

This is your "SIP username", you phone

Your name

If you have more than one phone concetor (the green one) specify one, otherwise it makes no difference

Press "apply" when done,

SpeedTouch - SIP - Mozilla Firefox

Bestand Bewerken Beeld Geschiedenis Bladvijzers Extra Help

https://192.168.1.254/cgi/bj_voip_xcig/?be=0&l0=2&l1=2

THOMSON ST706

Go to the "Expert Configure" menu

THOMSON
images & beyond

SpeedTouch [admin] Overview | Details | Configure | Expert Configure | Help

Home > Toolbox > Telephony

Broadband Connection

Toolbox

- Remote Assistance
- Address Book
- **Telephony**
- Game & Application Sharing
- Parental Control
- Firewall
- Intrusion Detection
- Dynamic DNS
- User Management

Home Network

Telephony

Service Configuration

Registrar: 85.119.188.3

Registrar Port: 5060

Proxy: 85.119.188.3

Proxy Port: 5060

Expire Time: 3600

Apply Cancel

Pick a task...

- > [view telephony statistics and logs](#)
- > [Address book](#)

Enter the SIP server (85.119.188.3) in the registrar and also in the proxy field

Klaar


1000+

Press "Apply" when done. The device will make a "click" sound if it works and the LED "voice" at the front will become stable green,

SpeedTouch - SIP - Mozilla Firefox

Bestand Bewerken Beeld Geschiedenis Bladwijzers Extra Help


http://192.168.1.254/cgi/bj_voip_cfg/?be=0&l0=2&l1=2

THOMSON ST706 


[admin] [Overview](#) | [Details](#) | [Configure](#) | [Expert Configure](#) | [Help](#)

[Home](#) > [Toolbox](#) > [Telephony](#)

Telephony





- Service Configuration
 - Enable Telephony: Apply Cancel
- Telephone Numbers

User Name	URI	Display Name	Abbr. Number	Port	Registered	
024 [redacted]	3starsnet.com	Jean-Louis Michel	024 [redacted]	Phone 1		Edit Delete
						Add

Pick a task...

- > [View telephony statistics and logs](#)
- > [View telephony services](#)
- > [Address book](#)



Klaar 

And that should do it. At least if you internet conection is up.